

Frequency	Kenwood LH FRS		Kenwood XLS FRS/GMRS		Kenwood XL FRS/GMRS		Motorola T6500 FRS/GMRS		Motorola T7400 FRS/GMRS	
	Channel	Output Power	Channel	Output Power	Channel	Output Power	Channel	Output Power	Channel	Output Power
462.5625	1	1/2W	1	1W	1	2W	1	1W	1	2W
462.5875	2	1/2W	2	1W	2	2W	2	1W	2	2W
462.6125	3	1/2W	3	1W	3	2W	3	1W	3	2W
462.6375	4	1/2W	4	1W	4	2W	4	1W	4	2W
462.6625	5	1/2W	5	1W	5	2W	5	1W	5	2W
462.6875	6	1/2W	6	1W	6	2W	6	1W	6	2W
462.7125	7	1/2W	7	1W	7	2W	7	1W	7	2W
467.5625	8	1/2W	—	—	—	—	8	1/2W	8	1/2W
467.5875	9	1/2W	—	—	—	—	9	1/2W	9	1/2W
467.6125	10	1/2W	—	—	—	—	10	1/2W	10	1/2W
467.6375	11	1/2W	—	—	—	—	11	1/2W	11	1/2W
467.6625	12	1/2W	—	—	—	—	12	1/2W	12	1/2W
467.6875	13	1/2W	—	—	—	—	13	1/2W	13	1/2W
467.7125	14	1/2W	—	—	—	—	14	1/2W	14	1/2W
462.5750	—	—	8	1W	8	2W	16	1W	16	2W
462.6250	—	—	9	1W	9	2W	18	1W	18	2W
462.6750	—	—	10	1W	10	2W	20	1W	20	2W
462.5500	—	—	11	1W	11	2W	15	1W	15	2W
462.6000	—	—	12	1W	12	2W	17	1W	17	2W
462.6500	—	—	13	1W	13	2W	19	1W	19	2W
462.7000	—	—	14	1W	14	2W	21	1W	21	2W
462.7250	—	—	15	1W	15	2W	22	1W	22	2W

Note that while the channel numbers and their corresponding frequencies do not match up between brands (above channel 14), the frequencies on all radios are the same. Simply match the channel frequencies with the chart above.

Contact us with any questions you may have concerning this information at 888-851-4327.